




DNH AS	DNH WW Ltd
Phone + 47 35 98 56 00	Phone + 44 1908 275 000
E-maildnh@dnh.nc	Fax+ 44 1908 275 100
Web-site www.dnh.nc	E-maildnh@dnh.co.uk


CAPEEX-6(T)x2 <u>RMANY</u>

NGLAND	GEI
NH WW Ltd	DN
hone+ 44 1908 275 000	Pho
ax+ 44 1908 275 100	Fax

DNH GMBH		
Phone + 49 040 6569 30-0		
Fax + 49 040 6569 30-30		
E-maildnh@dnh.de		


<u>USA</u>
DNH Speakers Inc
Phone+ 1 484 494 5790
Fax+ 1 484 494 5793
F-mail dnh@dnhsneakers.com





Certified by/ Certification code / Number: NEMKO / EEx de IIB+H2 T6 Gb / Nemko 10 ATEX 1054 IECEx NEM 11.0016





M20 Ex approved plastic blinding plugs

Specifications	
Material / Color	Aluminum / anodized
Mounting	Foot bracket
Termination	e-chamber, screw terminals
Weight w/transformer	3,8 kg
IP-rating	54
Max. / min. amb. temp	40°C / -20°C
Rated / max. power	3 W / 6 W
SPL 1W/1m	81 dB
SPL rated power	85 dB
Effective freq. range	190 – 20000 Hz
Dispersion (-6dB) 1kHz / 4kHz	
Directivity factor, Q	
Options	Impedances, labels

Installation, Operation and Maintenance Procedures

- Two separate loudspeakers, two transformers and two terminals in one Ex housing (A & B system).
- Enter the e-chamber by loosening the screws on the lid and terminate the cables in the screw terminals.
- Connect the speakers to the same phase.
- Fasten loudspeaker to wall or ceiling with three screws.
- Fasten lid screws with a torque of 2Nm to assure the IP rating.
- For optimum performance, always use the correct voltage / power and operate within the frequency limits as
- Use only certified/specified cable glands and blanking plugs.
- Standard model delivered with four M20 Ex approved plastic blinding plugs.
- Do not open loudspeaker when energized.
- Ex-loudspeakers must be earthed correctly using the specially marked screws.
- This loudspeaker is supplied with two years warranty against defective materials and workmanship.

CE